

## Giro radio remote control set

Product number: 7051086

Configuration: black

### Configuration options

7051086 | black


- ✓ Remote control
- ✓ 500 mm
- ✓ 100–240 V

GIRO is a wireless control system consisting of a single-channel remote control with a replaceable battery and a receiver unit. The GIRO receiver unit is connected directly to the main power supply.

For switching transformers, power supplies and lights.

The remote control, equipped with two buttons and a central indicator light, switches the lights connected to the power supply unit on and off, which in turn are connected to the receiver. Using GIRO, configurations with multiple control units (up to 3) can be set up and the control units can be operated by more than one remote control device (up to 9).

- wall-mounted transmitter with 10 m range
- receiver with 1800 mm mains connection line with flat European plug and 500 mm connection line with European socket
- remote control black, receiver white
- voltage 100–240 VAC, 600 watts



[more infos...](#)

### Technical data

Article type	Remote control	Length of connection cable (secondary)	1.800 mm
Height	16,5 mm	Length of the supply line (primary)	500 mm
Width	42 mm	Consisting of	Complete system with transmitter and receiver, including mounting material and batteries (long life, low energy consumption)
Mains voltage	100–240 V	Multiple radio remote controls possible	Yes
Plug type	Flat plug	Transmitter range	10 m
Max. connected load	600 watt	Remote control design	Radio remote control/wall switch with two switches
Connectivity	radio		