



FW function converter

Product number: 7061283
Configuration: module 3 (Bluetooth + radio), 60 W, 6-way distributor

Configuration options

7061271 | module 2 (radio), 30 W, 6-way distributor
7061273 | module 2 (radio), 60 W, 6-way distributor
7061281 | module 3 (Bluetooth + radio), 30 W, 6-way distributor
7061283 | module 3 (Bluetooth + radio), 60 W, 6-way distributor
7061286 | module 2 (radio), 15 W, 4-way distributor
7061287 | module 3 (Bluetooth + radio), 15 W, 4-way distributor

✓ 60 watts
✓ Bluetooth
✓ radio

The FW function converter for colour change lighting systems.
— white
— 12 VDC
— max. 36 watt load per slot on the converter
— 2000 mm mains connection line
— **switchable by Bluetooth app (module 3) or by optionally available radio remote control**

more infos...

Technical data

Article type	converter	Length of the supply line (primary)	2.000 mm
Height	16,2 mm	LIC system compatible	Yes
Width	315 mm	Output voltage	12 VDC
Power	60 watts	Luminaire slots	6
Connectivity	Bluetooth radio	Illuminant power	60 watts
Shape	angular		

Naber GmbH
Enschedestr. 24
DE-48529 Nordhorn

Tel. +49 5921 704-0
Fax +49 5921 704-140
naber@naber.com