



FW function converter

Product number: 7061286
Configuration: module 2 (radio), 15 W, 4-way distributor

Configuration options
7061271 | module 2 (radio), 30 W, 6-way distributor
7061273 | module 2 (radio), 60 W, 6-way distributor
7061281 | module 3 (Bluetooth + radio), 30 W, 6-way distributor
7061283 | module 3 (Bluetooth + radio), 60 W, 6-way distributor
7061286 | module 2 (radio), 15 W, 4-way distributor
7061287 | module 3 (Bluetooth + radio), 15 W, 4-way distributor

✓ 15 watts
✓ radio
✓ Luminaire slots: 4

The FW function converter for colour change lighting systems.
— white
— 12 VDC
— max. 36 watt load per slot on the converter
— 2000 mm mains connection line
— **switchable by Bluetooth app (module 3) or by optionally available radio remote control**

more infos...

Technical data

Article type	converter	Shape	angular
Height	16 mm	Length of the supply line (primary)	2.000 mm
Width	196,6 mm	LIC system compatible	Yes
Power	15 watts	Output voltage	12 VDC
Connectivity	radio	Luminaire slots	4

Naber GmbH
Enschedestr. 24
DE-48529 Nordhorn

Tel. +49 5921 704-0
Fax +49 5921 704-140
naber@naber.com